

## Repair Finish

Art.: 04.3002.9999

Bottle 250 ml

Repair Finish is part of the Innotec Stone Chip Repair System and the Innotec Stone Chip Repair System - VW (VAS 6083A). It is a softening agent used to polish the paint-filled stone-chip damage flush with the original paintwork. It also provides shine and protection for stone chip repairs.



Base:	Mixture of waxes, silicones and solvents emulsified in water
Density:	989 kg/m <sup>3</sup>
Consistency:	Thick fluid
Viscosity:	± 900 mPa.s
Solvents:	Mixture of alcohol and esters
Flash point:	13°C
Additions:	Wax and oil
Application conditions:	+10°C to +30°C
Type of surface:	The most common paint systems
Surface preparation:	The surface must be clean, dry and free of grease. Clean the surface with Innotec <a href="#">Adhesion Activator</a> .
Application method:	Shake the bottle before use. Wrap a <a href="#">Multi Wipe</a> folded in two around the <a href="#">Blue Plastic Card</a> and apply a small amount of Repair Finish to this. Wrap a Multi Wipe around the yellow <a href="#">Polish Block</a> . Rub the card over the paint-filled stone-chip damage a few times until it reduces and then use the polishing block to polish the filled stone chip. When all the stone chips are treated, use a Multi Wipe to carefully rub in a thin layer of Repair Finish, with circular movements. After treatment allow the surface to dry and rub with a clean, dry Multi Wipe. Then treat the surface with a damp <a href="#">Inno-Cleaner</a> , rubbing with circular movements, and rub down with a Multi Wipe. See also the directions for use of the Innotec <a href="#">Stone Chip Repair System</a> .
Cleaning of hands:	With Innotec <a href="#">Safe Hand Clean Plus</a> and water
Shelf life:	24 months in original, unopened packaging
Storage conditions:	Store cool and dry
Type of batchcode:	F
EAN Code:	5400563023563

This technical info sheet replaces all previous versions.





All information is supplied without obligation and based on our knowledge and experience with the product under normal conditions. In practice, the information supplied can in no way replace the tests that need to be performed before first use of the product. Only prior testing of the product can prove whether the product is indeed suitable for the intended application (or not). Thus, we cannot accept any responsibility in case our products are not used in compliance with the advices given.

If the product should not meet the quality requirements, we will only reimburse up to a maximum of the purchase price of the product. We accept no responsibility whatsoever and shall under no circumstances be liable for damage or consequential loss arising from the use of the product.

For information concerning safe use and storage, please refer to the safety data sheet of the product concerned.

